

## M10-QP SERIES

### DUAL OUTPUT ADJUSTABLE DC POWER SUPPLY

#### Features

- . Output off function
- . Quad independent DC outputs
- . Independent, series and parallel variety output
- . Constant voltage and constant current
- . Low ripple and noise
- . Plastic panel
- . Four LED displays with 3 digits, selectable for two sets  
output voltage and current display simultaneously



**M10-QP305E**

#### Specifications

.Line Regulation: CV  $1 \times 10^{-4} + 3\text{mV}$  CC  $2 \times 10^{-3} + 3\text{mA}$

.Load Regulation: CV  $1 \times 10^{-4} + 4\text{mV}$  CC  $2 \times 10^{-3} + 5\text{mA}$

.Ripple & Noise: CV  $1\text{mVrms}$  CC  $3\text{mA rms}$

.Display Accuracy:  $\pm 0.5\% \text{Rdg} + 2\text{digits}$

.Input Voltage:  $110 \sim 127\text{VAC} \pm 10\%$ ,  
 $220 \sim 240\text{VAC} \pm 10\%$  Switchable

Model	Independent Output	Series Output	Parallel Output	Dimensions (LxWxD)	Weight (kg)
M10-QP303E	CH1/0~30V/0~3A	CH1+CH2 0~60V/0~3A	CH1//CH2 0~30V/0~6A	260x160x310mm	10
	CH2/0~30V/0~3A		CH3/3~6.5V/3A		
	CH3/3~6.5V/3A	CH4/8~15V/1A	CH4/8~15V/1A		
	CH4/8~15V/1A	A	A		
M10-QP305E	CH1/0~30V/0~3A	CH1+CH2 0~60V/0~5A	CH1//CH2 0~30V/0~10A	260x160x310mm	12
	CH2/0~30V/0~3A		CH3/3~6.5V/3A		
	CH3/3~6.5V/3A	CH4/8~15V/1A	CH4/8~15V/1A		
	CH4/8~15V/1A	A	A		